settina. thereafter:

From 1500 MSL to 3800 MSL: - continue climb at not greater than V_{2F} + 10 KT.

At 3800 MSL:

accelerate smoothly to en-route climb speed.

DEPARTURE ROUTE DESCRIPTION

TAKE-OFF RWY 30:

CRAYE 5D: Climb to 5000. Climb straight ahead, at DBK VOR 5 DME turn LEFT on track 154° to intercept DBK R-184 climbing to CRAYE intersection.

KATTI 5D: Climb to 5000. Climb straight ahead, at DBK VOR 5 DME turn left on track 240° to intercept DBK R-267 climbing to KATTI intersection.

NERRA 5D: Climb to 6100. Climb straight ahead, at KLP NDB intercept DBK VOR R-302 climbing to NERRA intersection. Cross KLP NDB at or above 3800.

CRAYE

L-12, H-15